

**HPG Hybrydowy nóż do zdejmowania izolacji
do 1 kV AC/1,5 kV DC****ZDJĘCIA**

Wykonanie i badania wyrobu zgodnie z normą: PN-EN IEC 60900:2018-10

Regulacja głębokości nacięcia: 0÷5 mm
Masa: 180 g

Tolerancje długości i masy wynoszą $\pm 2\%$. Z powodu ciągłego rozwoju wyrobu, wygląd produktu może nieznacznie odbiegać od przedstawionego na zdjęciach.

OPIS

Narzędzie hybrydowe. Część robocza wykonana ze stali narzędziowej. Izolacja osłony przewodnicy i ostrza wykonana z twardego poliamidu zbrojonego włóknem szklanym. Rękojeść wykonana całkowicie z materiału izolacyjnego, twardego poliamidu zbrojonego włóknem szklanym dodatkowo pokryta warstwą izolacji z plastisolu (PVC) w kolorze pomarańczowym.

ZASTOSOWANIE

Nóż do zdejmowania izolacji stosowany jest w pracach pod napięciem przemiennym do 1000 V lub napięciem stałym do 1500 V. Nóż przeznaczony jest do zdejmowania izolacji żył kabli. Głębokość nacięcia izolacji regulowana od 0 do 5 mm.

PRZECHOWYWANIE I KONSERWACJA

Nóż należy przechowywać w torbie lub skrzynce narzędziowej oddzielnie od innych narzędzi, aby uniknąć mechanicznych uszkodzeń. Nóż przechowywać w pomieszczeniach suchych z dala od źródeł ciepła, w atmosferze nieagresywnej chemicznie. Chronić przed działaniem promieni słonecznych.

Nóż powinien być czyszczony po każdorazowym użyciu. Do czyszczenia stosować suchą szmatkę. Przy silnym zabrudzeniu, nóż czyścić szmatką zwilżoną wodą z dodatkiem delikatnego detergentu lub szmatką zwilżoną preparatem ASOREL i dokładnie osuszyć.

**HPG Hybrydowy nóż do zdejmowania izolacji
do 1 kV AC/1,5 kV DC****SPRAWDZENIE**

Przed każdym rozpoczęciem pracy należy dokonać oględzin noża. Kontrolę okresową polegającą również na oględzinach przeprowadzać raz na rok.

Oględziny obejmują sprawdzenie:

- o braku widocznych wad noża,
- o braku widocznych uszkodzeń izolacji,
- o stanu ostrza i przewodnicy,
- o czytelności i kompletności oznakowania noża.

Nóż uszkodzony, silnie zużyty (mechaniczne uszkodzenia izolacji, wadliwe działanie itd.) lub zabrudzony nie może być użyty w pracach pod napięciem. W przypadku zawilgocenia, nóż należy dokładnie osuszyć przed użyciem.

UWAGA!

W przypadku wątpliwości po przeprowadzeniu oględzin, narzędzie powinno zostać poddane ponownemu badaniu wytrzymałości elektrycznej lub wycofane z użytkowania w pracach pod napięciem.

CZĘSTOTLIWOŚĆ BADAŃ

Sprawdzenie przed użyciem i kontrolę okresową przeprowadzać zgodnie z poniższą tabelą.

	SPRAWDZENIE	KONTROLA OKRESOWA
Przez kogo	Kierujący zespołem	Dozór
Kiedy	Przed każdorazowym użyciem	Raz na rok*
W jaki sposób	Wzrokowo (oględziny)	Wzrokowo (oględziny)

**jeżeli instrukcja organizacji prac pod napięciem nie stanowi inaczej*

HPG Hybrid Wire Stripper
up to 1 kV AC / 1,5 kV DC**PHOTOS**

Product compliant with the requirements of EN IEC 60900:2018 standard.

Setting the cutting depth: $0 \div 5$ mm
Weight: 180 g

Length and weight tolerances are $\pm 2\%$. Due to continuous product development, product appearance may differ slightly from that shown in the photos.

CHARACTERISTICS

Hybrid tool. Working part made of tool steel. Insulation for guide and blade sheath made of tough glass fiber reinforced polyamide. Handle completely made of insulating material, tough fiberglass reinforced polyamide, additionally covered with a layer of insulation made of plastisol (PVC) in orange.

APPLICATION

The wire stripper is used in live work up to 1000 V AC or up to 1500 V DC. The wire stripper is designed for stripping cable conductor insulation. Depth of insulation cut adjustable from 0 to 5 mm.

STORAGE AND MAINTENANCE

The wire strippers should be stored and transported in a bag or toolbox separately from other tools to avoid mechanical damage. Store the knives in dry rooms, away from heat sources, in a chemically non-aggressive atmosphere. Protect against sunlight.

The wire stripper should be cleaned after each use. Use a dry cloth for cleaning. When the tool becomes heavily soiled, use a cloth with ASOREL or suitable cleaning solvent and dry it thoroughly.

EXAMINATION

A visual inspection of the wire stripper should be made before each use. Carry out a periodic inspection, also by visual inspection, once a year.

HPG Hybrid Wire Stripper
up to 1 kV AC / 1,5 kV DC

Visual inspection includes checking:

- o no visible defects in the wire stripper,
- o no visible damage to the insulation,
- o the condition of the blade and guide bar,
- o the legibility and completeness of the wire stripper marking.

Wire stripper damaged, heavily worn (mechanical damage to insulation, malfunction, etc.) or dirty must not be used in live applications. In case of moisture, dry the wire stripper thoroughly before use.

CAUTION!

In case of doubt, after the visual inspection, the tool should be re-tested for electric strength or withdrawn from use in live work.

FREQUENCY TESTS

For check and periodic inspection to be carried out in according to table.

	CHECK	PERIODIC INSPECITON
Who	Manager of team	Supervision
When	Before use	Once a year
How	Visually (visual inspection)	Visually (visual inspection)

**Unless instructions say otherwise*